



***Tronical***  
**COMPONENTS**

# TRONICALTUNE

**WE ARE SPINNING HEADS!**

**MANUAL**

V 2.12

# TRONICAL TUNE - INDEX

»»»	<b>TRONICAL TUNE OVERVIEW</b>	<b>3</b>
»»»	<b>TRONICAL TUNE - INSERT/REPLACE BATTERY</b>	<b>4-5</b>
»»»	<b>TUNE CONTROLLER</b>	<b>6</b>
»»»	<b>GETTING STARTED</b>	
	INSTALL THE SYSTEM TO THE GUITAR	<b>7-8</b>
	STRING YOUR GUITAR	<b>9-12</b>
	STRING UP AND DOWN MODE	<b>13</b>
	HOW TO TUNE / ADDITIONAL INFO	<b>14</b>
	PERFORMANCE SPECIFICATION	<b>15</b>
»»»	<b>START TO TUNE</b>	
	MULTI-STRING / SINGLE-STRING TUNING	<b>16-17</b>
	SWITCH BETWEEN BANKS	<b>18</b>
	EXAMPLE	<b>19</b>
	BANK OVERVIEW	<b>20</b>
»»»	<b>FUNCTION MENU</b>	
	FUNCTION OVERVIEW	<b>21</b>
	CUSTOM TUNING   SAVING	<b>22-23</b>
	REFERENCE TUNING	<b>24</b>
	FIRMWARE VERSION	<b>25</b>
	BATTERY LEVEL	<b>26</b>
»»»	<b>CONFIGURATION MENU</b>	
	OVERVIEW	<b>27</b>
	ACCURACY MODE	<b>28</b>
	ROBOHEAD DELAY	<b>29</b>
	RESET MODE	<b>30</b>
	ROBOHEAD SPEED	<b>31</b>
	INTERFERENCE LEVEL	<b>32</b>
»»»	<b>SYSTEM CONFIGURATION (EXPERT MENU)</b>	<b>33-37</b>
»»»	<b>CHARGING THE BATTERY</b>	<b>38</b>
»»»	<b>LEGAL INFORMATION</b>	<b>39</b>

# TRONICAL TUNE - OVERVIEW

## 6 ROBOHEADS


WITH NEW SURFACE LOCKING MECHANISM

## LED-DISPLAY

(6 STRING LEDS, 1 MENU LED, 1 CHARGE LEVEL LED)


## BATTERY

EXCHANGEABLE, RECHARGEABLE  
3.7 VOLTS, LI-POLYMER, APPROX. 300 TUNINGS



## BLACK TUNING CONTROLLER

BLACK MOUNTING BOARD WITH ROBOHEAD GUIDANCE




**NAVIGATION UNIT**  
(UP, DOWN, LEFT, RIGHT, ENTER)

**ON/OFF/BACK**

## AVAILABLE SPARE PARTS




- »»» Li-Po BATTERY
- »»» CHARGER WITH WALL-PLUG
- »»» ROBOHEADS
- »»» TUNING CONTROLLER WITH MOUNTING BOARD
- »»» WRENCH, LOCK NUTS & RING WASHERS

# TRONICAL TUNE INSERT BATTERY



**ATTENTION:** USE CAUTION WHEN INSTALLING THE BATTERY. PAY ATTENTION TO THE SLOTTED DESIGN TO GUARANTEE PROPER ORIENTATION. SLIDE IN THE BATTERY WITH THE TIP SIDE ONLY.


DO NOT APPLY ANY FORCE AS YOU MAY CAUSE DAMAGE TO THE ELECTRONICS.




# TRONICAL TUNE REPLACE BATTERY

 **ATTENTION:** USE CAUTION WHEN INSTALLING THE BATTERY. PAY ATTENTION TO THE SLOTTED DESIGN TO GUARANTEE PROPER ORIENTATION. SLIDE IN THE BATTERY WITH THE TIP SIDE ONLY. DO NOT APPLY ANY FORCE AS YOU MAY CAUSE DAMAGE TO THE ELECTRONICS.

**1** PRESS ON THE BATTERY TO RELEASE.



**2** PULL OUT THE BATTERY



# EXPLANATION - TUNE CONTROLLER



**i** PUSH AND HOLD THE "OFF-BUTTON" TO SWITCH OFF THE SYSTEM.

## LED EXPLANATION DURING THE TUNING (e-E)

- : STRING IN TUNE
- : STRING NOT IN TUNE (PICK STRING)
- : FREQUENCY OUT OF PITCH WINDOW
- : RESPECTIVE ROBOHEAD IS IN MOVEMENT
- : FREQUENCY MEASUREMENT IN PROGRESS
- : INTERFERENCE BETWEEN LOWER AND HIGHER STRINGS

**i** MUTE LOWER STRINGS THAT ARE IN TUNE AND STRUM HIGHER STRINGS AGAIN.

## LED EXPLANATION (BAT)

- : BATTERY FULLY CHARGED
- : BATTERY IS LOW
- : BATTERY IS EMPTY

## LED EXPLANATION (MENU)

- : TUNING IS ACTIVE
- : CONFIGURATION MENU
- : FUNCTION MENU
- : SYSTEM CONFIGURATION

## BLINKING MENU LED

- : ACOUSTIC GUITAR
- : ELECTRIC GUITAR

## GETTING STARTED INSTALL THE SYSTEM TO THE GUITAR



**NOTE:** DO NOT USE ANY TOOLS TO FIX THE LOCK NUT DO NOT OVER TIGHTEN. USE A **1 CENT COIN** TO TIGHTEN THE LOCKNUT, OTHERWISE YOU MAY DAMAGE THE GEAR WHEELS!



USE ONLY SUPPLIED WRENCH OR TORQUE WRENCH TO TIGHTEN THE HEX NUTS (THE RECOMMENDED TORQUE FOR THE HEX NUTS OF THE ROBOHEADS IS 1,5 NM - 1,65 NM ( 13.27 IN.LBS - 14.6 IN-LBS))

**IT IS RECOMMENDED TO USE A CONTACT CLEANING LIQUID BEFORE INSTALLING THE ROBOHEADS TO THE PCB BOARD AND TO ALSO NOT OVER TIGHTEN THE HEX NUTS BEFORE ENSURING ALL CONTACTS ARE MAKING A GOOD CONNECTION.**

**BE CAREFUL WHEN INSTALLING BATTERY AND PAY ATTENTION TO THE SLOTTED DESIGN TO GUARANTEE PROPER ORIENTATION!**

# GETTING STARTED INSTALL THE SYSTEM TO THE GUITAR



AT FIRST REMOVE ALL ORIGINAL TUNERS FROM THE HEADSTOCK.



PLACE THE CONTACTING PCB ONTO THE BACKSIDE OF THE HEADSTOCK. MAKE SURE THAT THE TRONICAL LOGO APPEARS THE RIGHT WAY UP.



MAKE SURE THAT ALL PCB DRILL HOLES LINE UP WITH THE HEADSTOCK'S TUNER HOLES. STICK THE ROBOHEADS THROUGH THE TUNER HOLES.



APPLY THE WASHERS AND MOUNT THE HEX NUTS.



USE THE WRENCH THAT COMES WITH THE SET TO TIGHTEN THE HEX NUTS OF THE ROBOHEADS.

*The recommended torque for the Hex Nuts of the Robo-Heads is 1.5 nm - 1.65 nm (13.27 in.lbs - 14.6 in.lbs)*



NOW TRONICALTUNE IS READY FOR STRING UP.





## GETTING STARTED STRING UP YOUR GUITAR

**MAX. RECOMMENDED STRING GAUGES: .013 .017 .026 .035 .045 .056 (THIRTEEN TO FIFTY-SIXES)**

**NOTE: HIGHER STRING GAUGES MAY CAUSE DAMAGE TO THE TUNERS!**

**PLEASE NOTE THE BASS SIDE ROBOHEADS TURN IN THE OPPOSITE DIRECTION FROM USUAL. THEY NOW TURN CLOCKWISE TO SHARPEN AND COUNTERCLOCKWISE TO FLATTEN.**

# GETTING STARTED >>> HOW TO USE THE STRING SHAFT WITH SURFACE LOCKING MECHANISM




**NOTE:** DO NOT USE ANY TOOLS TO FIX THE LOCK NUT DO NOT OVER TIGHTEN. USE A **1 CENT COIN** TO TIGHTEN THE LOCKNUT, OTHERWISE YOU MAY DAMAGE THE GEAR WHEELS!



USE ONLY SUPPLIED WRENCH OR TORQUE WRENCH TO TIGHTEN THE HEX NUTS (**MAX. 1NM TORQUE**)

- 1 LOCK NUT:** YOU NEED THE LOCK NUT TO TIGHTEN THE STRING.
- 2 STRING SHAFT:** THE STRING SHAFT WINDS THE STRING.
- 3 STRING RECESS:** THE STRING RECESS GUIDES THE STRING.
- 4 HEX NUT:** USE THE WRENCH WHICH COMES WITH THE SET TO TIGHTEN THE HEX NUTS OF THE ROBOHEADS.



# GETTING STARTED **»»»** HOW TO USE THE STRING SHAFT (BASS)



1




TAKE OFF THE LOCK NUT AND MAKE SURE THAT THE RECESS IS AT 90 DEGREES TO LONGITUDINAL DIRECTION OF THE NECK. YOU CAN TURN THE KEY MANUALLY OR USE THE STRING-UP MODE. WIND THE STRING AROUND THE STRING SHAFT UNDER THE RECESS AND BRING IT UP THROUGH THE RECESS.

2



WIND UP THE STRING CLOCKWISE AROUND THE STRING SHAFT ONCE ABOVE THE RECESS.


3



HOLD THE STRING TIGHT AND APPLY THE LOCK NUT.

**NOTE:** TRONICALTUNE SYSTEMS TYPE C (SIX-IN-A-ROW TUNER HEADSTOCKS) DO WORK WITH "BASS" ROBOHEADS ONLY.

4



TIGHTEN THE LOCK NUT WITH A SMALL COIN EASILY BY HAND.

**NOTE:** DO NOT USE ANY TOOL TO FIX THE LOCK NUT AND **DO NOT OVER TIGHTEN!** USE A 1 CENT COIN TO TIGHTEN THE LOCK NUT, OTHERWISE YOU MAY DAMAGE THE ROBO-HEAD!

RECOMMENDED MAX. TORQUE IS 1.0 NM (8.85 IN-LBS)

5




CUT THE END OF THE STRING CLOSE TO THE STRING SHAFT.

# GETTING STARTED HOW TO USE THE STRING SHAFT (TREBLE)



1



TAKE OFF THE LOCK NUT AND MAKE SURE THAT THE RECESS IS AT 90 DEGREES TO LONGITUDINAL DIRECTION OF THE NECK. YOU CAN TURN THE KEY MANUALLY OR USE THE STRING-UP MODE. WIND THE STRING AROUND THE STRING SHAFT UNDER THE RECESS AND BRING IT UP THROUGH THE RECESS.

2



WIND THE STRING AROUND THE SHAFT ONCE ABOVE THE RECESS.


3



HOLD THE STRING TIGHT AND APPLY THE LOCK NUT.

**NOTE:** TO ENSURE THAT THE 1ST (E) AND 2ND (B) STRING ARE SECURELY LOCKED, WE RECOMMEND TO PERFORM **TWO WINDINGS** AROUND THE STRING SHAFT BEFORE TIGHTENING THE LOCK NUT.

4




TIGHTEN THE LOCK NUT WITH A SMALL COIN EASILY BY HAND.

**NOTE:** DO NOT USE ANY TOOL TO FIX THE LOCK NUT AND **DO NOT OVER TIGHTEN!** USE A 1 CENT COIN TO TIGHTEN THE LOCK NUT, OTHERWISE YOU MAY DAMAGE THE ROBO-HEAD!

RECOMMENDED MAX. TORQUE IS 1.0 NM (8.85 IN-LBS)

5



CUT THE END OF THE STRING CLOSE TO THE STRING SHAFT.

# FUNCTION MENU E **STRING UP AND DOWN MODE**

FOR RESTRINGING YOUR GUITAR



**PUSH "ON" button.** The system activates the last completed tuning in **MULTI-STRING MODE**.

**PUSH "BACK" button** to enter **TUNING SELECTION MODE**. **MENU LED** is **OFF**.

**TO ENTER FUNCTION MENU**

**PRESS AND HOLD THE "UP" button** until **MENU LED** lights up **WHITE**.

**SELECT WHITE "E" -LED. PUSH "ENTER" to confirm.**  
The **MENU LED** switches **OFF**, The **"E"** lights up **RED**.

**PRESS "DOWN" to unwind** the low **"E"** string or **PRESS "UP"** to wind up the low **"E"** string.

**PRESS "LEFT/RIGHT" button** to choose any other string to wind up or down in the same manner.

**PRESS "BACK" for FUNCTION MENU.**



**DURING "STRING UP AND DOWN MODE" THE "SINGLE-STRING TUNING MODE" IS ACTIVE. IT IS RECOMMENDED TO WIND THE STRING ROUGHLY (+- 300 CENT) TO STANDARD PITCH, THEN RELEASE THE UP/DOWN BUTTON AND PLUCK THE STRING. THE SYSTEM TAKES OVER AND WILL TUNE THE STRING TO STANDARD PITCH AND AUTOMATICALLY MOVE TO THE NEXT STRING.**



**IMPORTANT!**  
**REFER to Page 36 to SELECT GUITAR TYPE (ACOUSTIC or ELECTRIC INSTALLATION)**

**SEE ADDITIONAL FUNCTIONS PG. 19**

# GETTING STARTED HOW TO TUNE / ADDITIONAL INFORMATION

## RE-TUNING

- 1** (STRUM BY THUMB, CLOSE TO THE NECK JOINT (SOUND HOLE), 1 STRUM = ALL STRINGS WITHIN 1 SEC.)
- 2** WAIT 3-5 SECONDS BETWEEN TWO STRUMS
- 3** AFTER STRUMMING, MUTE STRINGS THAT ARE ALREADY IN TUNE (GREEN LED LIT UP ON TUNE CONTROLLER) AND STRUM THE OUT-OF-TUNE STRINGS ONLY.

## CHANGE TUNING

- 1** To change the actual tuning (e.g. from Standard to DADGAD) you can select the **“SINGLE-STRING MODE”** or the **“MULTI-STRING MODE”** .

**SINGLE STRING MODE** is activated by PRESS AND HOLD **“ENTER”**

**MULTI- STRING MODE** is activated with a PUSH, **“ON”** button (for details please refer to “Tune Mode [page 15](#) and following”).

**SINGLE STRING MODE** is recommended to get familiar with the system and when you use the system in loud environments with ambient noise (especially with acoustic guitars).

**MULTI-STRING MODE** is recommended as the default mode as soon as you are used to the system.



**PLEASE NOTE THE BASS SIDE ROBOHEADS TURN IN THE OPPOSITE DIRECTION FROM USUAL. THEY NOW TURN CLOCKWISE TO SHARPEN AND COUNTERCLOCKWISE TO FLATTEN.**

# GETTING STARTED PERFORMANCE SPECIFICATION

## 1) BEST PERFORMANCE UNDER FOLLOWING CONDITIONS:

\* FOLLOW THE MANUAL FROM PAGE 3 TO PAGE 14!!

\* FOR THE BEST TUNING PERFORMANCE MAKE SURE THAT THE STRINGS ARE NOT STICKING IN THE NUT (STRING FRICTION).

\* THE INTONATION OF 12<sup>TH</sup> FRET FINGERED TO 12<sup>TH</sup> FRET HARMONIC SHOULD BE CORRECT

\* FOR STANDARD TUNING 440 HZ

\* DETUNING WITHIN THE NOMINAL +/- 30 CENT RANGE.


\* WITH A GOOD BATTERY CHARGE, EG. "BAT" INDICATOR IS GREEN

\* ACCURACY SET TO STANDARD, 3 LEDS (+/- 2.5 CENT ACCURACY)

		MIN	NOM	MAX	UNIT
<b>TUNING TIME</b>	SINGLE-STRING MODE	3	5	10	sec per string
	MULTI-STRING MODE	3	10	20	sec all strings








		MIN	NOM	MAX	UNIT
<b>NUMBER OF STRUMS</b>	SINGLE-STRING MODE	1	2	4	strums per string
	MULTI-STRING MODE	1	3	5	strums all strings

# START TO TUNE >>> TUNE MODE - MULTI-STRING TUNING



- 1- PRESS "ON". The **MULTI-STRING MODE** activates the last completed tuning.
- 2- Strum ALL strings once (**within 1sec.**)
- 3- Wait 3-5 seconds and mute the strings with your hand.
- 4- Mute the strings that are already in tune (**GREEN**).
- 5- Pick only the out-of-tune strings (**RED**)

IT IS IMPORTANT TO STRUM THE SAME WAY ALWAYS AT THE SAME POSITION NEAR THE END OF THE NECK WITH EITHER YOUR THUMB, FINGER OR PICK.

-  : STRING IN TUNE
-  : STRING NOT IN TUNE (PICK STRING)
-  : FREQUENCY OUT OF PITCH WINDOW
-  : RESPECTIVE ROBOHEAD IS IN MOVEMENT
-  : FREQUENCY MEASUREMENT IN PROGRESS
-  : INTERFERENCE BETWEEN LOWER AND HIGHER STRINGS
-  MUTE LOWER STRINGS THAT ARE IN TUNE AND STRUM HIGHER STRINGS AGAIN.




PRESS & HOLD "ENTER" TO CHANGE TO SINGLE STRING MODE.

IF THE TUNING IS COMPLETED THE SYSTEM TURNS OFF AUTOMATICALLY.



# START TO TUNE >>> TUNE MODE - SINGLE-STRING TUNING



1- **PRESS & HOLD "ON"**. The **SINGLE STRING MODE** activates the last completed tuning.



If you are in **TUNING SELECTION MODE** already, select the desired **PRESET**, then **PRESS & HOLD "ENTER"** for single string tuning.

2- **PICK ONE STRING AT A TIME** as indicated until all strings are in tune (**GREEN**).



**PRESS "LEFT" OR "RIGHT" TO SELECT THE STRING YOU WOULD LIKE TO TUNE.**



**MUTE STRINGS THAT ARE ALREADY IN TUNE (GREEN).**




**SEE LED EXPLANATION ON PAGE 4 OR SEE MULTI-STRING TUNING**

**WHEN THE TUNING IS COMPLETED THE SYSTEM TURNS OFF AUTOMATICALLY.**

# START TO TUNE >>> TUNING SELECTION

## >>> SWITCH BETWEEN RED, GREEN AND BLUE BANKS



**PRESS "ON"**. The **MULTI-STRING MODE** activates the last completed tuning.

Now **PRESS "BACK"** on the tuner controller for **TUNING SELECTION**. The **MENU LED** will switch **OFF**.

**PRESS "UP/DOWN"** to navigate between the **RED** (Standard), **GREEN** (Major) and **BLUE** (User) Banks. Each bank holds 6 tunings.

**PRESS "LEFT/RIGHT"** to select any Tuning (E-e)

**SINGLE-CLICK ON "ENTER"** to activate the selected tuning in **MULTI-STRING MODE** or **PRESS AND HOLD "ENTER"** for **SINGLE-STRING MODE**.

The **MENU LED** will light up **BLUE**.

# START TO TUNE >>> TUNING SELECTION

## >>> EXAMPLE: "OPEN G" MAJOR CHORD



**PUSH "ON"** button, the system will come up with the last completed tuning.  
**PUSH "BACK"** to enter the **TUNING SELECTION MODE**. The **MENU LED** switches **OFF**.

**PUSH "UP"** or **"DOWN"** to navigate to the **GREEN** (Major) Bank.



THE RESPECTIVE COLOR IS INDICATED BY THE COLOR OF THE STRING LED'S

**PUSH "LEFT/RIGHT"** until **G-LED** is shining **GREEN**.

**SINGLE-CLICK "ENTER"** for **MULTI-STRING MODE** or **PUSH & HOLD "ENTER"** for **SINGLE-STRING MODE**

Once the tuning is activated the RoboHeads start immediately in order to change the pitch. Keep your hands away from RoboHeads and strings during this automatic move phase (0.5 to 2 seconds).



**AFTER ALL ROBOHEADS HAVE STOPPED:**

**MUTE ALL STRINGS & PICK THE INDICATED OUT OF TUNE STRING (RED)** or **STRUM ALL OUT OF TUNE STRINGS (MULTI STRING MODE)** to start fine tune phase.

**MUTING THE „IN TUNE“ STRINGS (GREEN)** while tuning is also recommended to improve accuracy. If all strings are in tune the system switches off automatically.

# START TO TUNE >>> TUNING SELECTION

## >>> BANK OVERVIEW



### THE RED BANK

	E6 <sup>th</sup>	A5 <sup>th</sup>	D4 <sup>th</sup>	G3 <sup>rd</sup>	B2 <sup>nd</sup>	e1 <sup>st</sup>
<b>E</b> "STANDARD"	E2	A2	D3	G3	B3	E4
<b>A</b> "DADGAD"	D2	A2	D3	G3	A3	D4
<b>D</b> "WHOLE STEP"	D2	G2	C3	F3	A3	D4
<b>G</b> "DROP-D"	D2	A2	D3	G3	B3	E4
<b>B</b> "E-FLAT"	E <sub>b</sub> 2	A <sub>b</sub> 2	D <sub>b</sub> 3	G <sub>b</sub> 3	B <sub>b</sub> 3	E <sub>b</sub> 4
<b>e</b> "DOUBLE DROP-D"	D2	A2	D3	G3	B3	D4

### THE GREEN BANK

	E6 <sup>th</sup>	A5 <sup>th</sup>	D4 <sup>th</sup>	G3 <sup>rd</sup>	B2 <sup>nd</sup>	e1 <sup>st</sup>
<b>E</b> "OPEN E"	E2	B2	E3	G#3	B3	E4
<b>A</b> "OPEN A"	E2	A2	E3	A3	C#4	E4
<b>D</b> "OPEN D"	D2	A2	D3	F#3	A3	D4
<b>G</b> "OPEN G"	D2	G2	D3	G3	B3	D4
<b>B</b> "DOBRO"	G2	B2	D3	G3	B3	D4
<b>e</b> "ALL 4TH"	E2	A2	D3	G3	C4	F4

### THE BLUE BANK


	E6 <sup>th</sup>	A5 <sup>th</sup>	D4 <sup>th</sup>	G3 <sup>rd</sup>	B2 <sup>nd</sup>	e1 <sup>st</sup>
<b>E</b> "USER-DEFINED 01"	E2	A2	D3	G3	B3	E4
<b>A</b> "USER-DEFINED 02"	E2	A2	D3	G3	B3	E4
<b>D</b> "USER-DEFINED 03"	E2	A2	D3	G3	B3	E4
<b>G</b> "USER-DEFINED 04"	E2	A2	D3	G3	B3	E4
<b>B</b> "USER-DEFINED 05"	E2	A2	D3	G3	B3	E4
<b>e</b> "USER-DEFINED 06"	E2	A2	D3	G3	B3	E4



THE DEFAULT FOR ANY TUNING IN THE BLUE BANK IS STANDARD TUNING. TO SAVE USER-DEFINED TUNINGS, SEE "FUNCTION MENU - CUSTOM TUNING"

# FUNCTION MENU FUNCTION OVERVIEW

 STRING UP AND DOWN MODE / CUSTOM TUNING /  
REFERENCE TUNING / FIRMWARE VERSION / BATTERY LEVEL



PUSH **"ON"** button. The system activates the last completed tuning in **MULTI-STRING MODE**.

PUSH **"BACK"** button to enter the **TUNING SELECTION MODE**. **MENU LED** is OFF.

TO ENTER **FUNCTION MENU**:

PRESS AND HOLD THE **"UP"** button until **MENU LED** lights up **WHITE**.

PRESS **"LEFT/RIGHT"** to navigate through the **FUNCTION MENU (E, A, D, G, B)**.

PRESS **"ENTER"** to confirm or PRESS **"BACK"** for **TUNING SELECTION MODE**.

## FUNCTION MENU OVERVIEW

- E** STRING UP AND DOWN MODE (PG. 11)
- A** CUSTOM TUNING MODE (PG. 20-21)
- D** REFERENCE TUNING (PG. 22)
- G** FIRMWARE VERSION (PG 23)
- B** BATTERY LEVEL (PG. 24)

# FUNCTION MENU A CUSTOM TUNING



TUNE YOUR GUITAR MANUALLY IN ORDER TO SAVE THE TUNING ON A PRESET POSITION (BLUE BANK)

PUSH **"ON"** BUTTON the system comes up with the last completed tuning in **MULTI-STRING MODE**.

PUSH **"BACK"** button to enter **TUNING SELECTION MODE**. **MENU LED** is **OFF**.

TO ENTER **FUNCTION MENU**:


PRESS AND **HOLD THE "UP"** button until **MENU LED** lights up **WHITE**.  
PRESS **"LEFT/RIGHT"** button to **SELECT WHITE "A"-LED** and PRESS **"ENTER"**.

PICK THE STRING INDICATED BY THE **RED BLINKING LED** starting with low **"E"**. Measurement begins indicated by quick **YELLOW FLASHING "E"-LED**. Upon completion the **"E"-LED** will light up solid **GREEN**.

**MUTE THE "E" STRING** and **PROCEED WITH THE "A" STRING** in the same manner and so forth until all strings are measured (**GREEN**).

**CONTINUE ON NEXT PAGE...**

EXAMPLE:



ETC.

# FUNCTION MENU A CUSTOM TUNING | SAVING



Upon completion of measurement the system switches to the **BLUE** (User) bank automatically indicated by the **BLUE FLASHING LED**.

**PUSH "LEFT/RIGHT"** to select one of the six preset positions (E-e)  
**PUSH "ENTER"** to save your tuning.

**ALL STRING LED'S WILL FLASH GREEN TWO TIMES FOR CONFIRMATION.**

The system switches back to **FUNCTION MENU** automatically.  
 The **MENU LED** lights up **WHITE**.

**PUSH "BACK"** for **TUNING SELECTION MENU** or  
**PUSH AND HOLD "BACK"** to **SWITCH THE SYSTEM OFF**.

THE ACTUAL FREQUENCY RANGE LIMITS ARE AS FOLLOWS:


<b>E</b>	60	-	102 HERTZ
<b>A</b>	80	-	135 HERTZ
<b>D</b>	115	-	180 HERTZ
<b>G</b>	150	-	240 HERTZ
<b>B</b>	200	-	310 HERTZ
<b>e</b>	250	-	375 HERTZ



**YOU CAN SAVE CUSTOM TUNINGS IN THE BLUE BANK ONLY. YOU CAN SELECT YOUR CUSTOM TUNING IN THE SAME MANNER AS ANY OTHER TUNING.**



# FUNCTION MENU **D** REFERENCE TUNING



## SEQUENCE

- 1) TUNE THE GUITAR TO THE DESIRED TUNING PRESET.
- 2) CHANGE THE PITCH OF ONE STRING (REFERENCE STRING) BY MANUALLY TURNING THE KEY.
- 3) ENTER AND EXECUTE REFERENCE MODE

## TO ENTER REFERENCE TUNING MODE:

PUSH **"ON"** button. The system activates the last completed tuning in **MULTI-STRING MODE**.  
PUSH **"BACK"** button to enter **TUNING SELECTION MODE**. **MENU LED** is **OFF**.

PRESS AND HOLD THE **"UP"** button until the **MENU LED** lights up **WHITE**.  
PRESS **"LEFT/RIGHT"** button to **SELECT THE WHITE "D"-LED**.

PRESS **"ENTER"** for **REFERENCE TUNING MODE**. The **MENU LED** switches **OFF**.  
**E-LED FLASHES RED**.

PRESS **"LEFT/RIGHT"** button to **SELECT THE REFERENCE STRING**.

**PLUCK YOUR REFERENCE STRING** measurement begins indicated by quick **FLASHING YELLOW LED** of respective string. Upon completion the respective led lights up **GREEN** and all others are shining **RED**.

## STRUM ALL STRINGS (MULTI-STRING MODE).

The system will tune your guitar to the selected tuning preset in relation to the measured reference pitch.



THE LATEST COMPLETED REFERENCE TUNING IS AVAILABLE ON START-UP UNTIL YOU COMPLETE ANY OTHER TUNING.

SHOULD YOU WISH TO STORE YOUR REFERENCE TUNING REFER TO "CUSTOM TUNING" PAGE 23-24.



# FUNCTION MENU **G** FIRMWARE VERSION



PUSH "ON" button. The system turns on with the last completed tuning activated in **MULTI-STRING MODE**.

PUSH "**BACK**" button to enter **TUNING SELECTION MODE**. **MENU LED IS OFF**.

TO ENTER **FUNCTION MENU**:

PRESS AND **HOLD** "**UP**" until **MENU LED** lights up **WHITE**.

PRESS "**LEFT/RIGHT**" button to **SELECT WHITE "G"-LED** and PRESS "**ENTER**".

**LED'S START FLASHING THREE TIMES, ONE TIME FOR EACH OF THE THREE FIRMWARE VERSION DIGITS. THE FIRST DIGIT NUMBER IS **GREEN**, THE SECOND **BLUE** AND THE THIRD **RED**. EACH COLOR SYMBOLIZES VALUES FROM 1-6 ACCORDING TO THE DIGITS.**



ZERO IS SYMBOLIZED IF ALL LED'S ARE WHITE.

**EXAMPLE:** LED'S FLASH THREE TIMES

**FLASH: 1**



**VERSION:**


**1**

**FLASH: 2**



**6**

**FLASH: 3**



**0**

# FUNCTION MENU **B** **BATTERY LEVEL**



**PUSH "ON"** button. The system activates the last completed tuning in **MULTI-STRING MODE**.

**PUSH "BACK"** button to enter **TUNING SELECTION MODE**. **MENU LED** is **OFF**.

**PRESS AND HOLD THE "UP"** button until the **MENU LED** lights up **WHITE**.

**PRESS "LEFT/RIGHT"** button to **SELECT WHITE LED-B** and **PRESS "ENTER"**.


A FULLY CHARGED BATTERY DISPLAYS ALL LED'S AS SHOWN LEFT.



IF THE BATTERY IS LOW (**YELLOW**), THE ROBOHEADS WILL LOSE PERFORMANCE. IF ONLY TWO RED LED'S (A & E) ARE DISPLAYED, CHARGE THE BATTERY IMMEDIATELY.

# CONFIGURATION MENU >>> OVERVIEW

>>> ACCURACY LEVEL / ROBOHEAD DELAY /  
RESET / ROBOHEAD SPEED / INTERFERENCE LEVEL



PUSH **"ON"** button. The system tunes on with the last completed tuning in **MULTI-STRING MODE**.

PUSH **"BACK"** button to enter the **TUNING SELECTION MODE**. MENU LED is OFF.

TO ENTER **CONFIGURATION MENU**:

PRESS AND **HOLD** THE **"DOWN"** button until the **MENU LED** and **"E"** TURN **LIGHT BLUE**.

PRESS **"LEFT/RIGHT"** BUTTON TO SELECT THE DESIRED FUNCTION.

## CONFIGURATION MENU OVERVIEW

- A** ACCURACY LEVEL (PG. 29)
- D** ROBOHEAD DELAY (PG. 30)
- G** RESET (PG. 31)
- B** ROBOHEAD SPEED (PG. 32)
- e** INTERFERENCE LEVEL (PG. 33)

# CONFIGURATION MENU **A** ACCURACY MODE



**EXAMPLE:** HIGHEST ACCURACY LEVEL

PUSH **"ON"** button. The system comes up with the last completed tuning in **MULTI-STRING MODE**.

PUSH **"BACK"** button to enter **TUNING SELECTION MODE**. MENU LED IS OFF.

TO ENTER **CONFIGURATION MENU**:

PRESS AND **HOLD "DOWN"** button until MENU and **"E"** LED TURN **LIGHT BLUE**.

To access **ACCURACY MODE** SELECT THE **"A"-LED** and PRESS **"ENTER"**.

ACCURACY :

e	B	G	D	A	E	
+/-	+/-	+/-	+/-	+/-	+/-	
1.0	1.5	2.0	2.5	3.0	3.5	CENT

PRESS **"LEFT/RIGHT"** for desired accuracy level

PUSH **"ENTER"** to confirm



THE DEFAULT IS +/- 2.5 CENT (3 LED'S E-A-D).

THE HIGHEST ACCURACY LEVEL (ALL LED'S LIT UP SHOWN LEFT) WILL **INCREASE TUNING TIME**.

A LOWER ACCURACY LEVEL WILL **DECREASE TUNING TIME**.

# CONFIGURATION MENU

## D ROBOHEAD DELAY

SET THE START-DELAY OF THE ROBOHEADS.



EXAMPLE: MAX DELAY



WHEN YOU CHANGE A TUNING THE ROBOHEADS WILL START WORKING IMMEDIATELY IN ORDER TO CHANGE THE PITCH. WITH THIS FUNCTION YOU CAN DELAY THE START UP TO 2.5 SECONDS.

PUSH **"ON"** button. The system turns on with the last completed tuning in **MULTI-STRING MODE**.

PUSH **"BACK"** button to enter the **TUNING SELECTION MODE**. MENU LED is OFF.

### TO ENTER CONFIGURATION MENU

PRESS AND HOLD **"DOWN"** button until MENU LED and **"LED-E"** LED TURN **LIGHT BLUE**.



THE DEFAULT IS NO DELAY (ALL LED'S ON).

PRESS **"LEFT/RIGHT"** to select desired delay level.  
PRESS **"ENTER"** to confirm.

All String LED'S FLASH **GREEN** TWICE to confirm that the **SELECTED DELAY LEVEL** has been stored.

PUSH **"BACK"** to access **CONFIGURATION MENU**.

THE MAX DELAY LEVEL AS SHOWN LEFT WILL DELAY THE START OF THE ROBOHEADS BY 2.5 SEC.

EACH ADDITIONAL LED DECREASES THE DELAY BY 0.5 SEC.

# CONFIGURATION MENU **RESET**



PUSH **"ON"** button. The system turns on with the last completed tuning in **MULTI-STRING MODE**.

PUSH **"BACK"** button to enter **TUNING SELECTION MODE**. MENU LED is OFF.

TO ENTER **CONFIGURATION MENU**  
PRESS AND **HOLD "DOWN"** button until MENU LED and **"E" LED** TURN **LIGHT BLUE**.

TO ACCESS **RESET** SELECT **"G"-LED** and PRESS **"ENTER"**.

SELECT **"E"-LED** for the reset of all **CUSTOM TUNINGS**.

SELECT **"A"-LED** for **FACTORY RESET** (all data).

To confirm PRESS AND **HOLD "UP"** and PRESS AND **HOLD "ENTER"** at the same time.

## RESET STYLES OVERVIEW

-  RESET ALL CUSTOM TUNINGS
-  FACTORY RESET (RESET ALL DATA EXCEPT CUSTOMER TUNING DATA)

# CONFIGURATION MENU **B** **ROBOHEAD SPEED**

SETS THE SPEED OF THE ROBOHEADS FOR ALL TUNING MODES.



**EXAMPLE:** HIGHEST SPEED LEVEL



USE THIS FUNCTION TO SET THE SPEED (AND ACCELERATION) OF THE ROBOHEADS. IF THE NECK OF YOUR GUITAR NEEDS MORE TIME TO STABILIZE WHEN CHANGING TUNINGS, REDUCE THE SPEED.

**PUSH "ON"** button. The system turns on with the last completed tuning in **MULTI-STRING MODE**.

**PUSH "BACK"** button to enter the **TUNING SELECTION MODE**. **MENU LED** is OFF.

TO ENTER **CONFIGURATION MENU** **PRESS AND HOLD "DOWN"** button until **MENU** and **"E" LED** TURN **LIGHT BLUE**.

TO ACCESS **ROBOHEAD SPEED** SELECT **"B"-LED** and **PRESS "ENTER"**.



LESS ROBOHEAD SPEED CAN DECREASE STRESS TO THE STRINGS AND TO THE GUITAR NECK.

IN CASE OF FREQUENT STRING SNAPPING OR NO STABLE TUNING RESULTS AFTER LONG DISTANCE TUNINGS DUE TO NECK RELIEF, TRY A LOWER SPEED LEVEL.

SELECT ROBOHEAD SPEED BY PUSHING **"LEFT/RIGHT"**.  
**PRESS "ENTER"** to confirm.



THE DEFAULT IS SET TO THE HIGHEST SPEED LEVEL AS SHOWN LEFT (ALL LED'S ON).

# CONFIGURATION MENU INTERFERENCE LEVEL



EXAMPLE: HIGHEST INTERFERENCE LEVEL.



A GUITAR STRING IS NOT ONLY PRODUCING NOT ONLY THE FUNDAMENTAL FREQUENCY BUT ALSO SEVERAL OVERTONES (E.G. THE E STRING IS PRODUCING 82.41 HERTZ AS FUNDAMENTAL AND OVERTONES AT 164.82, 247.23 AND SO FORTH).

THAT MEANS THAT THE E-STRING IS INTERFERING WITH THE B-STRING BECAUSE THE SECOND OVERTONE OF THE E-STRING AND THE FUNDAMENTAL OF THE B-STRING INTERFERE AROUND 247 HERTZ.

WHEN YOU RECOGNIZE THAT THE ROBOHEAD OF THE B STRING IS TURNING WITHOUT PLUCKING THE B-STRING REDUCE THE INTERFERENCE LEVEL. IF YOUR GUITAR IS NOT PRODUCING PRONOUNCED OVERTONES YOU CAN INCREASE THE INTERFERENCE LEVEL TO IMPROVE PERFORMANCE.

**PUSH "ON"** button. The system turns on with the last completed tuning in **MULTI-STRING MODE**.

**PUSH "BACK"** button to enter the **TUNING SELECTION MODE**. MENU LED IS OFF.

To enter **CONFIGURATION MENU** PRESS AND **HOLD "DOWN"** BUTTON until MENU and "E" LED TURN **LIGHT BLUE**.

TO ACCESS **INTERFERENCE LEVEL** SELECT "e"-LED and PRESS "ENTER".



SETS THE GLOBAL INTERFERENCE LEVEL FOR ALL TUNING MODES.


DEFAULT IS 3-LEDS

**PUSH "LEFT/RIGHT"** to select between a high and low interference level to prevent that the harmonic of a low string is recognized as the pitch-level of a high string.



# SYSTEM CONFIGURATION >>> OVERVIEW

>>> GAIN / GUITAR TYPE / PITCH WINDOW / DOUBLE CLICK



THE SYSTEM CONFIGURATION MENU IS USED TO CONFIGURE SYSTEM RELEVANT PARAMETERS LIKE GUITAR-TYPE, GAIN AND FREQUENCY SNAP. THE CLICKSTREAM TO ENTER THIS MENU IS MORE COMPLICATED TO PREVENT UNINTENDED CHANGES. THESE SETTINGS ARE AFFECTING THE SYSTEM'S PERFORMANCE AND ACCURACY. PLEASE STEP GENTLY.

**PUSH "ON"** button. The system turns on with the last completed tuning in MULTI-STRING MODE.

**PUSH "BACK"** button to enter TUNING SELECTION MODE. MENU LED IS OFF.

**TO ENTER SYSTEM CONFIGURATION** PRESS AND **HOLD "RIGHT"** and **"ENTER"** at the same time.

"MENU"-LED and "E"-LED LIGHT UP **YELLOW**.


**PRESS "LEFT/RIGHT"** to navigate through the menu (E, A, D).

**PRESS "ENTER"** to confirm or **PRESS "BACK"** for TUNING SELECTION MODE.

## SYSTEM CONFIGURATION OVERVIEW

- E** → GAIN (PG. 32)
- A** → GUITAR TYPE (PG. 33)
- D** → PITCH WINDOW (PG.34)
- G** → SINGLE OR DOUBLE CLICK FOR TUNE (PG. 35)

# SYSTEM CONFIGURATION **E** GAIN SETTINGS



TRONICAL TUNE HAS A SUPERIOR DYNAMIC RANGE TO SENSE THE SOLID-BORNE SOUND OF YOUR INSTRUMENT (>130DB). THIS IS ACHIEVED BY A PIEZO TRANSDUCER, A DYNAMICAL ADJUSTABLE AMPLIFIER AND A 24 ANALOG TO DIGITAL CONVERTER (ADC). WITH THE "GAIN SETTING" THE STARTING POINT OF THE AMPLIFIER IS SET. FROM THIS STARTING POINT THE AMPLIFIER IS ADJUSTED DURING THE TUNING PROCESS IN THE RANGE OF +-9DB.



WHEN YOU PERFORM A "CALIBRATION" A GOOD STARTING POINT FOR THE AMPLIFIER IS SET. YOU CAN OVERRIDE THE GAIN SETTING WITH THIS FUNCTION. BE CAREFUL WHEN CHANGING THE GAIN!

INCREASE THE GAIN IF STRINGS ARE NOT RECOGNIZED WHEN PLUCKED (STRING LED IS NOT GETTING YELLOW, STRING IS NOT TUNED) OR SIGNAL IS FADING OUT TOO QUICK.  
DECREASE THE GAIN IF THE GUITAR IS TOO SENSITIVE OR IF USED IN LOUD ENVIRONMENTS WITH AMBIENT NOISE.  
GAIN LEVEL : 2.5DB, 6DB, 9DB, 12DB, 15DB, 18DB

PUSH "ON" button. The system turns on with the last completed tuning in MULTI-STRING MODE.

PUSH "BACK" button to enter TUNING SELECTION MODE. MENU LED IS OFF.

TO ENTER **SYSTEM CONFIGURATION**

PRESS AND HOLD "RIGHT" and "ENTER" at the same time.

"MENU"-LED AND "E"-LED LIGHT UP **YELLOW**.

SELECT THE PIEZO SIGNAL LEVEL BY PUSHING "LEFT/RIGHT".


PUSH "ENTER" to confirm.

PUSH "BACK" for **SYSTEM CONFIGURATION MENU**.



THE DEFAULT IS 3 LEDS AND WILL BE ADAPTED WHEN EXECUTING CALIBRATION MODE. SELECTING A DIFFERENT LEVEL WILL AFFECT SYSTEM PERFORMANCE OR CAN CAUSE MALFUNCTION.

# SYSTEM CONFIGURATION **A** GUITAR TYPE



**i** GREEN "E" & BLUE "A" BLINKING LED'S:  
ACOUSTIC GUITAR

**i** GREEN "E," BLUE "A," & RED "D" BLINKING LED'S:  
SHORT FRET GUITAR

**i** IT IS IMPORTANT TO SETUP THE SYSTEM TO THE CORRECT GUITAR TYPE. ACOUSTIC GUITARS ARE EQUIPPED WITH THICKER STRINGS AND SHOW DIFFERENT ACOUSTIC CHARACTERISTICS.

Push "**ON**" button. The system turns on with the last completed tuning in **MULTI-STRING MODE**.

Push "**BACK**" button to enter **TUNING SELECTION MODE**. "**MENU**" LED is OFF.

To enter **SYSTEM CONFIGURATION**:

PRESS and HOLD "**RIGHT**" and "**ENTER**" AT THE SAME TIME.

"**MENU**"-LED and "**E**"-LED LIGHT UP **YELLOW**.

For **GUITAR TYPE** select "**A**"-LED and press "**ENTER**".

The **DEFAULT SETTING** is **LED-E** for "ELECTRIC."

Use the "LEFT/RIGHT" button to change to the appropriate setting:

1. **GREEN "E"** (ELECTRIC)
2. **GREEN "E" & BLUE "A"** (ACOUSTIC)
3. **GREEN "E," BLUE "A," & RED "D"** (SHORT FRET GUITARS)

Press "**ENTER**" to **CONFIRM**.

# SYSTEM CONFIGURATION **D** **PITCH WINDOW**



**EXAMPLE:**

Every time when a tuning is completed the system stores the actual pitch for each string. On re-tune the system checks if the actual string frequencies are within a certain PITCH WINDOW. If a string is outside its Pitch Window the corresponding LED turns purple. If at least one string is out of its Pitch Window the system automatically switches to **SINGLE TUNE MODE** after the remaining strings are tuned.

The Pitch Window can be adjusted from 25 to 150 Cent.

**PITCH WINDOW**


e	B	G	D	A	E	
25	35	50	75	100	150	CENT

**PRESS "LEFT/RIGHT"** for desired PITCH WINDOW.  
**PRESS "ENTER"** to confirm.



DEFAULT IS 75 CENT = 4 LEDS.

**EXAMPLE:**


THE PITCH WINDOW IS SET TO 100CENT=5LEDS. THE LAST COMPLETED TUNING WAS A STANDARD EADGBE. NOW THE SYSTEM IS STARTED AGAIN. IF THE PITCH OF THE LOW E STRING IS MORE THAN 100CENT OFF, THE CORRESPONDING E-LED WOULD BECOME MAGENTA  (LOWER THAN EB OR HIGHER THAN F).

# SYSTEM CONFIGURATION **G** SINGLE OR DOUBLE CLICK FOR TUNE



 GREEN FLASHING "E" LED :  
SINGLE CLICK (DEFAULT)

 GREEN "E" & BLUE "A" BLINKING LED'S:  
DOUBLE CLICK

 SELECT BETWEEN SINGLE CLICK OR DOUBLE CLICK TO ACTIVATE TUNING.

**SINGLE CLICK:** PRESS ONCE TO CONFIRM SELECTED TUNING

**DOUBLE CLICK:** PRESS TWICE TO CONFIRM SELECTED TUNING (MORE TIME TO REMOVE HAND OUT OF THE SYSTEM / ROBOHEADS)

Push the "ON" button. The system turns on with the last completed tuning in **MULTI-STRING MODE**.  
Push the "BACK" button to enter **TUNING SELECTION MODE**. The "MENU" LED is off.

To enter **SYSTEM CONFIGURATION** **PRESS** and **HOLD** both "RIGHT" and "ENTER" **AT THE SAME TIME**.

The "MENU"-LED and "E"-LED light up **YELLOW**.

For **SINGLE OR DOUBLE CLICK TUNING**, SELECT "G"-LED and **PRESS "ENTER"**

Select either **LED-E** for "SINGLE CLICK" or **LED "A"** for "DOUBLE CLICK." **PRESS "ENTER"** to CONFIRM.

# TRONICAL TUNE CHARGING THE BATTERY



## BATTERY PACK

3.7V 340mAh 1258mWh LI-POLYMER

A BATTERY THAT HAS BEEN INFREQUENTLY USED, OR A NEW ONE, COULD HAVE REDUCED CAPACITY. YOU MAY NEED TO RECHARGE IT A NUMBER OF TIMES. WHEN THE BATTERY LEVEL IS LOW, THE BAT LED FLASHES RED.

### CAUTION:

1. DO NOT CONNECT IMPROPERLY.
2. DO NOT DISPOSE OF IN FIRE OR EXPOSE TO EXCESS HEAT.
3. DO NOT CRUSH, PUNCTURE, INCINERATE OR SHORT CIRCUIT EXTERNAL CONTACTS.



### CHARGING:

CHARGE THE BATTERY LATEST WHEN LED BAT IS SHINING RED.

## LI-POLYMER CHARGER

INPUT: AC100-240V 50/60HZ

OUTPUT: 4.2V  $\pm$  300mA



## BATTERY IS CHARGING




## BATTERY IS CHARGED



# LEGAL INFORMATION

## Guidelines for safe and efficient use.

 Read this information before using Tronical Tune.

## PRODUCT CARE:

**Do not** expose your product to liquid or moisture or to humidity.

**Do not** expose your product to extreme high or low temperatures.

**Do not** expose your product to lit candles, cigarettes, or cigars, or to open flames etc.

**Do not** drop, throw or try to bend the product as rough treatment could damage it.

**Do not** attempt to disassemble your product. The product does not contain consumer serviceable or replaceable components. Only Tronical GmbH should perform service.

If you will not be using the product for a while, store it in a place that is dry, free from damp, dust and extreme temperatures.

## DISPOSAL OF OLD ELECTRICAL & ELECTRONIC EQUIPMENT:



This symbol on the product indicates that this product shall not be treated as household waste. Instead it shall be handed over to the applicable collection point for the recycling of electrical and electronic equipment. By ensuring this product is disposed of correctly, you will help prevent potential negative consequences for the environment and human health, which could otherwise be caused by inappropriate waste handling of this product. The recycling of materials will help to conserve natural resources. For more detailed information about recycling of this product, please contact your local city office, your household waste disposal service or the shop where you purchased the product.

## POWER SUPPLY

Connect the AC power adapter only to designated power sources as marked on the product. To reduce risk of damage to electric cord, remove it from the outlet by holding onto the AC adapter rather than the cord. Make sure the cord is positioned so that it will not be stepped on, tripped over or otherwise subjected to damage or stress. To reduce risk of electric shock, unplug the unit from any power source before attempting to clean it. »

The AC power adapter must not be used outdoors or in damp areas. DANGER - Never alter the AC cord or plug. If the plug will not fit into the outlet, have a proper outlet installed by a qualified electrician. Improper connection can result in risk of electric shock.

## CHILDREN:

**Do not** allow children to play with Tronical Tune since it contains small parts that could become detached and create a choking hazard.

## BATTERY INFORMATION:

A rechargeable battery has long service life if treated properly. A new battery or one that has not been used for a long period of time could have reduced capacity the first few times it is used. Do not expose the battery to extreme temperatures, never above +55° C (+131° F). For maximum battery capacity, use the battery in room temperature. If the battery is used in low temperatures, the battery capacity will be reduced. The battery can only be charged in temperatures between +10°C (+50° F) and +45° C (+113° F).

## RECYCLING THE BATTERY:

The battery in your Tronical Tune must be disposed of properly and should never be placed in municipal waste.

## CAUTION:

1. DO NOT CONNECT IMPROPERLY.
2. DO NOT DISPOSE OF IN FIRE OR EXPOSE TO EXCESS HEAT.
3. DO NOT CRUSH, PUNCTURE, INCINERATE OR SHORT CIRCUIT EXTERNAL CONTACTS.





***Tronical***  
**COMPONENTS**

Tronical Components GmbH • Heselstücken 18 •  
D-22453 Hamburg Germany  
Web: [www.tronical.com](http://www.tronical.com) • Mail: [info@tronical-components.com](mailto:info@tronical-components.com)  
HRB 94503

© Copyright 2012 Tronical-Components GmbH. All rights reserved.